

# Company Switch

200A. 120/208V. Series 16 SafeCam® and Connection Chamber



- Electric power distribution center for theatre, convention centers, arenas and events centers
- Series 16 SafeCam® receptacles
- 200A. Main breaker rated 65K AIC
- SafeCam® system monitors receptacles and activates shunt trip whenever a plug is removed from a receptacle
- Connection chamber for bare-end cables. Door is electrically interlocked with main breaker shunt trip
- Options:
  - ✦ Dual neutral
  - ✦ Parallel sets of receptacles
  - ✦ Isolated Ground
  - ✦ Reverse Neutral / Ground
  - ✦ 1Ø - 120V., 120/240V.,
  - ✦ 3Ø - 277/480V., 208V., 480V.
  - ✦ Digital Meter
  - ✦ Custom color finish
  - ✦ Recessed or Pad mounting
  - ✦ Type 3R, 4 or 4X enclosure

**Catalog Number:** CSC-2010-SCSP

**Product Type:** Company Switch with Series 16 SafeCam® receptacles and connection chamber

**Main Enclosure:** TYPE 1, Steel, black wrinkled powder-coat finish, wall mounting brackets. Hinged access door to connection chamber, with lockable handle. Electrical interlock on door shall activate shunt trip in breaker when door is opened.

**Cable Entry:** Grommeted holes in bottom of enclosure for portable bare-end cable entry.

**Dimensions:** 28"H. x 21"W. x 8 3/4" D.

**Rating:** 200A., 120/208V., 3Ø, 4W+G

**Circuit Breakers:** Molded-case, UL489, 65K AIC @ 240V.,  
(1) 200A., 3-pole with shunt trip interlocked with connection chamber door

**Receptacles:** (5) Series 16 SafeCam® panel mount color coded receptacles with dummy plugs..

**Busbar Output:** (5) dual rated mechanical lugs on copper bus accessible in connection chamber

**Monitoring:** LED Indicator lights to indicate presence of phase voltage.

**Labelling:** Laser engraved cam identifiers and panel rating. Cable connection warning label per NEC Art 520.

**Listina:** UL Listed

Union Connector Co., Inc.  
Jacksonville, FL 32256  
631-753-9550

